

Summary

Single-phase buck-boost transformer. Steps down 120V to 95V at 80 amps continuous output. 7.6 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 120V building supply to 95V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 95V that is installed on a 120V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 80-amp buck-boost transformer is significantly smaller and lighter than a 80-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-120V-95V-80A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	7.6 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	120V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	63.30A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	95V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	80A	Winding Material	Aluminum
Maximum Primary OCP	80A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	52 lbs
Temperature Rise	115°C	Dimensions	7.68"-W x 6.38"-D x 12.2"-H

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Front View, Side View, and Top View.

Front View Dimensions:

- Overall Width: 12.21"
- Overall Height: 8.27"
- Top Flange Width: 6.58"
- Top Flange Height: 1.26"
- Distance between hole centerlines (top row): 2.95"
- Distance from left edge to first hole centerline: 1.14"
- Distance from last hole centerline to right edge: 1.14"
- Ground hole diameter: $\varnothing 0.2"$
- Ground hole location: 1.18" from right edge, 1.95" from bottom edge
- Bottom Flange Width: 7.68"
- Bottom Flange Height: 0.96"

Side View Dimensions:

- Overall Height: 14.36"
- Overall Width: 6.38"
- Top Flange Height: 4.25"
- Bottom Flange Height: 0.79"
- (1) 3/4" NPT Knockout Per Side, located 1.67" from left edge and 1.57" from bottom edge
- Four M3 holes, located 0.08" from left edge and 0.89" from bottom edge

Top View Dimensions:


- Overall Width: 7.68"
- Overall Height: 6.38"
- Distance between hole centerlines (left to right): 5.35"
- Distance between hole centerlines (top to bottom): 4.41"
- Distance from left edge to first hole centerline: 1.16"
- Distance from top edge to first hole centerline: 0.95"
- (4) 3/4" NPT Knockouts

Bottom (Underside) Plate

Connection Guide

1. Connect **X2** and **X3** together
2. Connect High Voltage **L1** to **X4**
3. Connect Low Voltage **L1** to **X1**, **H4**, **H3**
4. Connect High & Low Voltage **L2** to **H1** and **H2**

DIAGRAM B2





TX-BB-120V-95V-80A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core