



Summary

Single-phase buck-boost transformer. Steps down 133V to 120V at 25 amps continuous output. 3 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 133V building supply to 120V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 120V that is installed on a 133V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 25-amp buck-boost transformer is significantly smaller and lighter than a 25-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-133V-120V-3KVA — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	3 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	133V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	22.56A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	120V	Termination Access	(6) ½" NPT Hubs
Secondary Amperage	25A	Winding Material	Aluminum
Maximum Primary OCP	30A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	14 lbs
Temperature Rise	115°C	Dimensions	4.65"-W x 3.86"-D x 9.25"-H

Ratings & Certifications


- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View:

- Overall dimensions: 4.77" (width) x 5.32" (height).
- Two circular features (knockouts) at the top, each with a diameter of 0.82".
- Distance between the centers of the two top knockouts: 1.97".
- Ground hole with a diameter of $\varnothing 0.2$ ".
- Distance from the left edge to the center of the ground hole: 3.01".
- Distance from the bottom edge to the center of the ground hole: 1.18".
- Bottom edge features: 1.63" wide section with a 0.08" thick lip.
- Distance from the left edge to the center of the bottom edge feature: 1.95".
- Overall width at the bottom: 4.65".

Front View:

- Overall height: 10.97".
- Top flange height: 9.25".
- (1) 1/2" NPT Knockout on the right side, 1.89" from the top edge and 1.57" from the bottom edge.
- Bottom flange height: 4.17".
- Bottom flange width: 3.86".
- Bottom flange features: 0.39" wide section with a 0.08" thick lip.
- Distance from the left edge to the center of the bottom flange feature: 2.05".

Bottom View:

- Overall dimensions: 4.65" (width) x 3.86" (height).
- Four 1/2" NPT knockouts arranged in a 2x2 grid.
- Distance between the centers of the knockouts: 2.32" (horizontal) and 2.09" (vertical).
- Distance from the left edge to the center of the leftmost knockouts: 1.16".
- Distance from the bottom edge to the center of the bottommost knockouts: 0.98".

Connection Guide

1. Connect **X2** and **X3** together
2. Connect **H2** and **H3** together
3. Connect High Voltage **L1** to **X4**
4. Connect Low Voltage **L1** to **H4** and **X1**
5. Connect High & Low Voltage **L2** to **H1**

DIAGRAM D2





TX-BB-133V-120V-3KVA — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core