

Summary

Single-phase buck-boost transformer. Steps down 146V to 115V at 15 amps continuous output. 1.73 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 146V building supply to 115V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 115V that is installed on a 146V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 15-amp buck-boost transformer is significantly smaller and lighter than a 15-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-146V-115V-15A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	1.73 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	146V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	11.80A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	115V	Termination Access	(6) ½" NPT Hubs
Secondary Amperage	15A	Winding Material	Aluminum
Maximum Primary OCP	15A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	17 lbs
Temperature Rise	115°C	Dimensions	4.65 x 3.86 x 9.25

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View:

- Overall dimensions: 4.77" (width) x 5.32" (height) and 4.65" (width) x 9.25" (height).
- Top features: Two 1/2" NPT knockouts, 3.15" apart, with 1.97" center-to-center spacing. Mounting holes are 0.82" from the top edge.
- Bottom features: Ground hole (Ø 0.2"), 3.01" from the left edge. Mounting bracket with 1.18" and 0.08" dimensions. 1.63" and 1.95" dimensions for the bracket base. 0.86" dimension for the bracket height.

Front View:

- Overall dimensions: 10.97" (width) x 3.94" (height) and 9.25" (width) x 3.86" (height).
- Side features: (1) 1/2" NPT Knockout Per Side, 1.89" from the side edge. Mounting holes are 4.17" from the side edge.
- Bottom features: M3 mounting holes, 0.39" and 0.08" dimensions. 2.05" dimension for the bracket base. 3.86" dimension for the bracket width.


Bottom View:

- Overall dimensions: 4.65" (width) x 3.86" (height) and 2.09" (width) x 0.98" (height).
- Features: (4) 1/2" NPT knockouts, 2.32" apart, with 1.16" center-to-center spacing. Mounting holes are 0.98" from the bottom edge.

Connection Guide

1. Connect **X2** and **X3** together
2. Connect High Voltage **L1** to **X4**
3. Connect Low Voltage **L1** to **X1**, **H4**, **H3**
4. Connect High & Low Voltage **L2** to **H1** and **H2**

DIAGRAM B2





TX-BB-146V-115V-15A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core