

Summary

Single-phase buck-boost transformer. Steps up 200V to 230V at 65.22 amps continuous output. 15 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 200V building supply to 230V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 230V that is installed on a 200V system.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 65.22-amp buck-boost transformer is significantly smaller and lighter than a 65.22-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-200V-230V-15KVA — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	15 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	200V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	75.00A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	230V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	65.22A	Winding Material	Aluminum
Maximum Primary OCP	100A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	42 lbs
Temperature Rise	115°C	Dimensions	7.68"-W x 6.38"-D x 11.02"-H

Ratings & Certifications


- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View Dimensions:

- Overall Width: 7.68"
- Overall Height: 6.38"
- Central Cutout Width: 2.95"
- Central Cutout Height: 1.14"
- Distance from Left Edge to Cutout: 1.14"
- Distance from Right Edge to Cutout: 1.14"
- Distance from Top Edge to Cutout: 1.28"
- Distance from Bottom Edge to Cutout: 1.18"
- Ground Hole: $\varnothing 0.2"$
- Distance from Bottom Edge to Ground Hole: 1.18"
- Distance from Left Edge to Ground Hole: 1.95"
- Distance from Right Edge to Ground Hole: 0.86"
- Distance from Bottom Edge to Ground Hole: 0.08"

Front View Dimensions:

- Overall Width: 7.68"
- Overall Height: 6.38"
- Central Cutout Width: 2.95"
- Central Cutout Height: 1.14"
- Distance from Left Edge to Cutout: 1.14"
- Distance from Right Edge to Cutout: 1.14"
- Distance from Top Edge to Cutout: 1.28"
- Distance from Bottom Edge to Cutout: 1.18"
- Ground Hole: $\varnothing 0.2"$
- Distance from Bottom Edge to Ground Hole: 1.18"
- Distance from Left Edge to Ground Hole: 1.95"
- Distance from Right Edge to Ground Hole: 0.86"
- Distance from Bottom Edge to Ground Hole: 0.08"

Bottom View Dimensions:

- Overall Width: 7.68"
- Overall Height: 6.38"
- Central Cutout Width: 2.95"
- Central Cutout Height: 1.14"
- Distance from Left Edge to Cutout: 1.14"
- Distance from Right Edge to Cutout: 1.14"
- Distance from Top Edge to Cutout: 1.28"
- Distance from Bottom Edge to Cutout: 1.18"
- Ground Hole: $\varnothing 0.2"$
- Distance from Bottom Edge to Ground Hole: 1.18"
- Distance from Left Edge to Ground Hole: 1.95"
- Distance from Right Edge to Ground Hole: 0.86"
- Distance from Bottom Edge to Ground Hole: 0.08"

Notes:

- (1) 3/4" NPT Knockout Per Side
- (4) 3/4" NPT Knockouts

Connection Guide

1. Connect **X2** and **X3** together
2. Connect **H2** and **H3** together
3. Connect High Voltage **L1** to **X4**
4. Connect Low Voltage **L1** to **H4** and **X1**
5. Connect High & Low Voltage **L2** to **H1**

DIAGRAM D2



**Part # — TX-BB-200V-230V-15KVA**

Buck-Boost Transformer Specification Sheet

sales@sanzosales.com

Page 4 of 9



TX-BB-200V-230V-15KVA — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core