

Summary

Single-phase buck-boost transformer. Steps down 240V to 200V at 75 amps continuous output. 15 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 240V building supply to 200V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 200V that is installed on a 240V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 75-amp buck-boost transformer is significantly smaller and lighter than a 75-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-240V-200V-15KVA — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	15 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	240V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	62.50A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	200V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	75A	Winding Material	Aluminum
Maximum Primary OCP	80A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	60 lbs
Temperature Rise	115°C	Dimensions	7.68"-W x 6.38"-D x 12.2"-H

Ratings & Certifications


- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View:

- Overall dimensions: 12.21" (width) x 8.27" (height).
- Top section width: 6.58".
- Top section height: 1.26".
- Top section features: 6 mounting holes (3 on each side) with a center-to-center distance of 2.95".
- Side section width: 1.14" (on each side of the center).
- Bottom section width: 7.68".
- Bottom section height: 1.95".
- Bottom section features: 2 mounting holes with a center-to-center distance of 1.18".
- Ground hole: $\varnothing 0.2"$ hole, 1.18" from the right edge.
- Bottom section features: 2 mounting holes with a center-to-center distance of 0.96".

Front View:

- Overall dimensions: 14.36" (width) x 12.21" (height).
- Top section height: 8.47".
- Top section features: 6 mounting holes (3 on each side) with a center-to-center distance of 2.95".
- Side section width: 1.14" (on each side of the center).
- Bottom section width: 7.68".
- Bottom section height: 1.95".
- Bottom section features: 2 mounting holes with a center-to-center distance of 1.18".
- Ground hole: $\varnothing 0.2"$ hole, 1.18" from the right edge.
- Bottom section features: 2 mounting holes with a center-to-center distance of 0.96".

Bottom View:

- Overall dimensions: 7.68" (width) x 6.38" (height).
- Top section width: 5.35".
- Top section height: 1.16".
- Top section features: 4 mounting holes (2 on each side) with a center-to-center distance of 1.16".
- Side section width: 1.14" (on each side of the center).
- Bottom section width: 4.41".
- Bottom section height: 0.95".
- Bottom section features: 4 mounting holes (2 on each side) with a center-to-center distance of 1.16".

Labels:

- (1) 3/4" NPT Knockout Per Side
- (4) 3/4" NPT Knockouts
- Ground hole
- M3

Connection Guide

1. Connect **X4** and **X2** together
2. Connect High Voltage **L1** to **X4** and **X3**
3. Connect **X2** and **X1** together
4. Connect Low Voltage **L1** to **X1**, **X2**, **H4**, **H3**
5. Connect High & Low Voltage **L2** to **H1** and **H2**

DIAGRAM A2





TX-BB-240V-200V-15KVA — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core