

Summary

Single-phase buck-boost transformer. Steps up 240V to 264V at 104 amps continuous output. 27.46 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 240V building supply to 264V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 264V that is installed on a 240V system.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 104-amp buck-boost transformer is significantly smaller and lighter than a 104-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-240V-264V-104A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	27.46 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	240V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	114.00A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	264V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	104A	Winding Material	Aluminum
Maximum Primary OCP	150A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	52 lbs
Temperature Rise	115°C	Dimensions	7.68"-W x 6.38"-D x 12.2"-H

Ratings & Certifications


- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Front View, Side View, and Top View.

Front View Dimensions:

- Overall Width: 12.21"
- Overall Height: 8.27"
- Top Flange Width: 6.58"
- Top Flange Thickness: 1.26"
- Top Flange Spacing: 1.14" (between knockouts), 2.95" (between mounting holes), 1.14" (between mounting holes and edge)
- Ground Hole: $\varnothing 0.2"$, located 1.18" from the right edge and 1.95" from the bottom edge.
- Mounting Bracket: 1.95" wide, 0.86" high, with a 1.18" gap from the right edge.
- Bottom Flange Width: 7.68"

Side View Dimensions:

- Overall Height: 14.36"
- Top Flange Height: 12.21"
- Knockout Location: (1) 3/4" NPT Knockout Per Side, located 1.67" from the left edge and 1.57" from the bottom edge.
- Bottom Flange Height: 0.79"
- Bottom Flange Width: 6.38"
- Bottom Flange Thickness: 0.08"
- Bottom Flange Spacing: 0.89" (between knockouts), 1.38" (between mounting holes), 0.08" (between mounting holes and edge)
- Bottom Flange Mounting: M3

Top View Dimensions:

- Overall Width: 12.21"
- Overall Height: 8.27"
- Knockout Location: (4) 3/4" NPT Knockouts, located 1.16" from the left edge and 0.95" from the top edge.
- Knockout Diameter: $\varnothing 0.2"$

Bottom (Underside) Plate:

(4) 3/4" NPT Knockouts

Connection Guide

1. Connect **X4** and **X2** together
2. Connect High Voltage **L1** to **X4** and **X3**
3. Connect **X2** and **X1** together
4. Connect Low Voltage **L1** to **X1**, **X2**, **H4**, **H3**
5. Connect High & Low Voltage **L2** to **H1** and **H2**

DIAGRAM A2





TX-BB-240V-264V-104A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core