

Summary

Single-phase buck-boost transformer. Steps down 250V to 230V at 22.94 amps continuous output. 5.28 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 250V building supply to 230V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 230V that is installed on a 250V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 22.94-amp buck-boost transformer is significantly smaller and lighter than a 22.94-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-250V-230V-23A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	5.28 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	250V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	21.12A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	230V	Termination Access	(6) ½" NPT Hubs
Secondary Amperage	22.94A	Winding Material	Aluminum
Maximum Primary OCP	30A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	14 lbs
Temperature Rise	115°C	Dimensions	4.65"-W x 3.86"-D x 9.25"-H

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View:

- Overall dimensions: 4.77" (width) x 5.32" (height).
- Two circular features (knockouts) at the top, each with a diameter of 0.82".
- Distance between the centers of the two top knockouts: 1.97".
- Ground hole with a diameter of $\varnothing 0.2$ ".
- Distance from the left edge to the center of the ground hole: 3.01".
- Distance from the bottom edge to the center of the ground hole: 1.18".
- Bottom edge features: 1.63" wide section with a 0.08" thick lip.
- Distance from the left edge to the center of the bottom edge feature: 1.95".
- Overall width at the bottom: 4.65".

Front View:

- Overall height: 10.97".
- Top flange height: 9.25".
- (1) 1/2" NPT Knockout Per Side, located 1.89" from the left edge and 1.57" from the bottom edge.
- Distance from the left edge to the center of the knockout: 1.57".
- Distance from the bottom edge to the center of the knockout: 1.57".
- Bottom edge features: 3.86" wide section with a 0.08" thick lip.
- Distance from the left edge to the center of the bottom edge feature: 2.05".
- Distance from the bottom edge to the center of the bottom edge feature: 0.39".
- Overall width at the bottom: 3.86".

Bottom View:

- Overall dimensions: 4.65" (width) x 3.86" (height).
- Four circular features (knockouts) arranged in a 2x2 grid.
- Distance between the centers of the two top knockouts: 2.32".
- Distance between the centers of the two bottom knockouts: 2.09".
- Distance from the left edge to the center of the top-left knockout: 1.16".
- Distance from the bottom edge to the center of the bottom-left knockout: 0.98".
- Overall width at the bottom: 4.65".
- Overall height at the bottom: 3.86".

(4) 1/2" NPT Knockouts

Bottom (Underside) Plate

Connection Guide

1. Connect **X4** and **X3** together
2. Connect **X2** and **X1** together
3. Connect High Voltage **L1** to **X4**, **X3**
4. Connect Low Voltage **L1** to **X1**, **X2**, **H4**
5. Connect **H3** and **H2** together
6. Connect High & Low Voltage **L2** to **H1**

DIAGRAM C2





TX-BB-250V-230V-23A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core