

Summary

Single-phase buck-boost transformer. Steps down 276V to 230V at 70 amps continuous output. 16.1 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 276V building supply to 230V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 230V that is installed on a 276V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 70-amp buck-boost transformer is significantly smaller and lighter than a 70-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-276V-230V-70A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	16.1 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	276V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	58.30A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	230V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	70A	Winding Material	Aluminum
Maximum Primary OCP	80A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	60 lbs
Temperature Rise	115°C	Dimensions	7.68 x 6.38 x 12.2

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Front, Side, and Top.

Front View:

- Overall width: 12.21"
- Overall height: 8.27"
- Top flange width: 6.58"
- Top flange height: 1.26"
- Top flange features four circular knockouts, each with a diameter of $\varnothing 0.2$ ".
- Knockout spacing: 2.95" between centers.
- Ground hole: $\varnothing 0.2$ " diameter, located 1.18" from the bottom edge.
- Bottom flange width: 7.68"
- Bottom flange height: 1.95"
- Bottom flange features a central slot with a width of 0.96" and a depth of 0.86".

Side View:

- Overall width: 14.36"
- Overall height: 12.21"
- Top flange width: 6.58"
- Top flange height: 1.26"
- Knockout diameter: $\varnothing 0.2$ "
- Knockout spacing: 2.95" between centers.
- Bottom flange width: 7.68"
- Bottom flange height: 1.95"
- Bottom flange features a central slot with a width of 0.96" and a depth of 0.86".

Top View:

- Overall width: 12.21"
- Overall height: 8.27"
- Top flange width: 6.58"
- Top flange height: 1.26"
- Knockout diameter: $\varnothing 0.2$ "
- Knockout spacing: 2.95" between centers.
- Bottom flange width: 7.68"
- Bottom flange height: 1.95"
- Bottom flange features a central slot with a width of 0.96" and a depth of 0.86".

Bottom (Underside) Plate:

- Overall width: 12.21"
- Overall height: 8.27"
- Top flange width: 6.58"
- Top flange height: 1.26"
- Knockout diameter: $\varnothing 0.2$ "
- Knockout spacing: 2.95" between centers.
- Bottom flange width: 7.68"
- Bottom flange height: 1.95"
- Bottom flange features a central slot with a width of 0.96" and a depth of 0.86".

Connection Guide

1. Connect **X2** and **X3** together
2. Connect High Voltage **L1** to **X4**
3. Connect Low Voltage **L1** to **X1**, **H4**, **H3**
4. Connect High & Low Voltage **L2** to **H1** and **H2**

DIAGRAM B2





TX-BB-276V-230V-70A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core