

Summary

Single-phase buck-boost transformer. Steps down 480V to 436V at 25 amps continuous output. 10.9 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 480V building supply to 436V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 436V that is installed on a 480V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 25-amp buck-boost transformer is significantly smaller and lighter than a 25-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-480V-436V-25A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	10.9 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	480V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	22.70A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	436V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	25A	Winding Material	Aluminum
Maximum Primary OCP	30A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	34 lbs
Temperature Rise	115°C	Dimensions	5.43 x 4.49 x 10.87

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View Dimensions:

- Overall Width: 5.43"
- Overall Height: 10.87"
- Mounting Hole Spacing: 2.95" (center-to-center)
- Mounting Hole Diameter: 1.12"
- Ground Hole Diameter: $\varnothing 0.2"$
- Ground Hole Spacing: 1.18"
- Ground Hole Diameter: 0.08"
- Ground Hole Spacing: 1.95"
- Ground Hole Diameter: 0.86"

Front View Dimensions:

- Overall Height: 13"
- Overall Width: 10.87"
- Knockout Diameter: (1) 3/4" NPT Knockout Per Side
- Knockout Spacing: 1.97"
- Knockout Diameter: 1.57"
- Knockout Spacing: 0.39"
- Knockout Diameter: 0.08"
- Knockout Spacing: 2.32"
- Knockout Diameter: 4.49"
- Knockout Diameter: M3

Bottom View Dimensions:

- Overall Width: 5.43"
- Overall Height: 4.45"
- Knockout Spacing: 1.1"
- Knockout Spacing: 3.23"
- Knockout Diameter: (4) 3/4" NPT Knockouts
- Knockout Spacing: 2.52"
- Knockout Diameter: 0.95"

Connection Guide

1. Connect **X2** and **X3** together
2. Connect **H2** and **H3** together
3. Connect High Voltage **L1** to **X4**
4. Connect Low Voltage **L1** to **H4** and **X1**
5. Connect High & Low Voltage **L2** to **H1**

DIAGRAM D2





TX-BB-480V-436V-25A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core