



Summary

Three-phase delta buck-boost transformer. Steps up 202V to 208V at 20.82 amps continuous output. 7.5 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 202V three phase building supply to 208V delta at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 208V that is installed on a 202V system experiencing undervoltage from the utility.

Configured as an open delta autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 20.82-amp buck-boost transformer is significantly smaller and lighter than a 20.82-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-202D-208D-7.5KVA — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Three Phase Delta (3-PH), AC	Transformer Type	Buck/Boost
Capacity	7.5 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	202V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	21.44A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	208V	Termination Access	(6) ½" NPT Hubs
Secondary Amperage	20.82A	Winding Material	Aluminum
Maximum Primary OCP	30A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	18 lbs
Temperature Rise	115°C	Dimensions	7.75"-W x 5.25"-D x 7.25"-H

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-5085 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.

Dimensions

Three-phase open delta installation — (2) enclosures required.



Connection Guide

1. Connect **X2** and **X3** together for both transformers
2. Connect **H2** and **H3** together for both transformers
3. Connect High Voltage **PHASE A** to **X4** on transformer A
4. Connect High Voltage **PHASE C** to **X4** on transformer B
5. Connect Low Voltage **PHASE A** to **H4** and **X1** on transformer A
6. Connect Low Voltage **PHASE C** to **H4** and **X1** on transformer B
7. Connect High & Low Voltage **PHASE B** to **H1**
8. Bridge **H1** connections between transformer A & B

DIAGRAM G2

HIGH VOLTAGE





sales@sanzosales.com

SANZO SALES

TX-BB-208D-230D-6.25A

Phase:	Single Phase	Configuration:	Autotransformer
Input Voltage:	208V	Max BCP:	6.25A
Output Voltage:	230V	Frequency:	60/50 Hz
Altitude range:	0 to 4000'	Insulation:	180°C
Max Input Amps:	24.00A	Temp Rise:	110°C
Max Output Amps:	6.25A	Windings:	Aluminum

Endurance Type MB-80-20 for Indoor or Outdoor Use
 Compliance to UL 508 Conformance to IEC 60084-21-20
 Serial # TX-BB-208D-230D-6.25A Lot # 400004

Autotransformer

CONFORMS TO UL 508, UL 508-1
 CONFORMS TO IEC 60084-21

SANZO SALES

TX-BB-208D-230D-6.25A

Phase:	Single Phase	Configuration:	Autotransformer
Input Voltage:	208V	Max BCP:	6.25A
Output Voltage:	230V	Frequency:	60/50 Hz
Altitude range:	0 to 4000'	Insulation:	180°C
Max Input Amps:	24.00A	Temp Rise:	110°C
Max Output Amps:	6.25A	Windings:	Aluminum

Endurance Type MB-80-20 for Indoor or Outdoor Use
 Compliance to UL 508 Conformance to IEC 60084-21-20
 Serial # TX-BB-208D-230D-6.25A Lot # 400004

Autotransformer

CONFORMS TO UL 508, UL 508-1
 CONFORMS TO IEC 60084-21

sales@sanzosales.com



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core