



Summary

Single-phase buck-boost transformer. Steps down 220V to 208V at 25 amps continuous output. 5.2 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 220V building supply to 208V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 208V that is installed on a 220V system experiencing overvoltage.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 25-amp buck-boost transformer is significantly smaller and lighter than a 25-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-220V-208V-25A — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	5.2 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	220V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	23.60A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	208V	Termination Access	(6) ½" NPT Hubs
Secondary Amperage	25A	Winding Material	Aluminum
Maximum Primary OCP	30A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	14 lbs
Temperature Rise	115°C	Dimensions	4.65"-W x 3.86"-D x 9.25"-H

Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the Bottom (Underside) Plate, showing three views: Top, Front, and Bottom.

Top View Dimensions:

- Overall Width: 4.77"
- Overall Height: 5.32"
- Inner Width: 4.65"
- Inner Height: 9.25"
- Top Knockout Spacing: 3.15" (center-to-center), 1.97" (edge-to-center)
- Top Knockout Diameter: $\varnothing 0.2"$
- Ground Hole: $\varnothing 0.2"$
- Slot Width: 1.95"
- Slot Depth: 0.86"
- Slot Position: 1.18" from right edge, 0.08" from bottom edge
- Bottom Edge: 1.63" from slot, 0.86" from bottom edge

Front View Dimensions:

- Overall Height: 10.97"
- Overall Width: 3.86"
- Knockout Diameter: (1) 1/2" NPT Knockout Per Side
- Knockout Position: 1.89" from top edge, 1.57" from bottom edge
- Knockout Spacing: 2.05" (center-to-center)
- Knockout Diameter: $\varnothing 0.39"$
- Knockout Position: 0.08" from right edge
- Knockout Type: M3

Bottom View Dimensions:

- Overall Width: 4.65"
- Overall Height: 3.86"
- Knockout Spacing: 2.32" (center-to-center), 1.16" (edge-to-center)
- Knockout Diameter: (4) 1/2" NPT
- Knockout Position: 2.09" from left edge, 0.98" from bottom edge

Connection Guide

1. Connect **X4** and **X3** together
2. Connect **X2** and **X1** together
3. Connect High Voltage **L1** to **X4**, **X3**
4. Connect Low Voltage **L1** to **X1**, **X2**, **H4**
5. Connect **H3** and **H2** together
6. Connect High & Low Voltage **L2** to **H1**

DIAGRAM C2





TX-BB-220V-208V-25A — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core