

Summary

Single-phase buck-boost transformer. Steps up 230V to 253V at 47.43 amps continuous output. 12 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

Product Description

This unit corrects a 230V building supply to 253V at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 253V that is installed on a 230V system.

Wired as an autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 47.43-amp buck-boost transformer is significantly smaller and lighter than a 47.43-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-230V-253V-12KVA — NEMA 3R Encapsulated, cETLus Listed

Specifications

Phase	Single Phase (1-PH), AC	Transformer Type	Buck/Boost
Capacity	12 kVA	Configuration	Encapsulated Autotransformer
Primary Voltage	230V	Primary Termination	Lead Wires & Terminal Lugs
Primary Amperage	52.17A	Secondary Termination	Lead Wires & Terminal Lugs
Secondary Voltage	253V	Termination Access	(6) ¾" NPT Hubs
Secondary Amperage	47.43A	Winding Material	Aluminum
Maximum Primary OCP	70A	Enclosure Material	Steel
Frequency	50/60 Hz	Finish Color	ANSI 70 Light Grey
Insulation	180°C	Weight	34 lbs
Temperature Rise	115°C	Dimensions	5.43"-W x 4.49"-D x 10.87"-H

Ratings & Certifications


- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-50 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

Important: Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.



Technical drawing of the bottom (underside) plate of a 1000W, 12VDC power supply. The drawing includes three views: a top view, a side view, and a bottom view.

Top View: The plate is 5.43" wide and 10.87" high. It features three mounting holes (1.12" diameter) spaced 2.95" apart, and a ground hole (0.2" diameter) located 1.18" from the bottom edge. The plate is 0.25" thick.

Side View: The plate is 10.87" high and 4.25" wide. It shows the (1) 3/4" NPT knockout per side, located 1.97" from the bottom edge. The plate is 0.25" thick.

Bottom View: The plate is 5.43" wide and 4.45" high. It features four 3/4" NPT knockouts arranged in a 2x2 grid, with dimensions 1.1" and 3.23" between them. The plate is 0.25" thick.

Connection Guide

1. Connect **X2** and **X3** together
2. Connect **H2** and **H3** together
3. Connect High Voltage **L1** to **X4**
4. Connect Low Voltage **L1** to **H4** and **X1**
5. Connect High & Low Voltage **L2** to **H1**

DIAGRAM D2





TX-BB-230V-253V-12KVA — NEMA 3R Encapsulated, cETLus Listed



Base Knockouts — (4) ¾" NPT



Side View



Rear View — Surface Mount Bracket



Wiring Compartment — Terminal Leads



Interior — Epoxy Resin Encapsulated Core