



### Summary

Three-phase delta buck-boost transformer. Steps up 440V to 480V at 14.43 amps continuous output. 12 kVA capacity. NEMA 3R enclosed, cETLus listed, wall mount.

### Product Description

This unit corrects a 440V three phase building supply to 480V delta at the point of use, permanently, without modifying the building's electrical service. Designed for equipment rated 480V that is installed on a 440V system experiencing undervoltage from the utility.

Configured as an open delta autotransformer, the unit handles only the difference between input and output and not the full load. This is why a 14.43-amp buck-boost transformer is significantly smaller and lighter than a 14.43-amp isolation transformer. The encapsulated core construction eliminates audible hum and provides stable thermal performance under continuous duty.

Features a removable wiring compartment door, removable knockout plate, and six NPT knockouts for flexible conduit entry. Surface mounting bracket for easy wall mount installations.



TX-BB-440D-480D-12KVA — NEMA 3R Encapsulated, cETLus Listed

### Specifications

|                     |                              |                       |                              |
|---------------------|------------------------------|-----------------------|------------------------------|
| Phase               | Three Phase Delta (3-PH), AC | Transformer Type      | Buck/Boost                   |
| Capacity            | 12 kVA                       | Configuration         | Encapsulated Autotransformer |
| Primary Voltage     | 440V                         | Primary Termination   | Lead Wires & Terminal Lugs   |
| Primary Amperage    | 15.75A                       | Secondary Termination | Lead Wires & Terminal Lugs   |
| Secondary Voltage   | 480V                         | Termination Access    | (6) ¾" NPT Hubs              |
| Secondary Amperage  | 14.43A                       | Winding Material      | Aluminum                     |
| Maximum Primary OCP | 20A                          | Enclosure Material    | Steel                        |
| Frequency           | 50/60 Hz                     | Finish Color          | ANSI 70 Light Grey           |
| Insulation          | 180°C                        | Weight                | 44 lbs                       |
| Temperature Rise    | 115°C                        | Dimensions            | 10.25"-W x 4.75"-D x 9.25"-H |

### Ratings & Certifications

- Listed for United States
- NEMA 3R Indoor/Outdoor Enclosure
- Built to UL-5085 Standards
- CE Certified
- Listed for Canada
- Epoxy Resin Encapsulated
- RoHS Compliant



### Common Applications

- HVAC & Minisplit
- Loads CNC Machines
- Pump Stations
- Packaging Machines
- Commercial Kitchen Equipment
- Motor Loads
- EV Chargers
- Server Racks & IT Equipment
- Refrigeration & Walk-in
- Coolers Fans & Blowers
- Conveyor Systems
- Overhead Doors

**Important:** Buck-boost transformers applied as autotransformers do not provide circuit isolation and do not create a neutral. Contact us if your application requires isolation or neutral creation.

## Dimensions

Three-phase open delta installation — (2) enclosures required.



## Connection Guide

1. Connect **X2** and **X3** together for both transformers
2. Connect **H2** and **H3** together for both transformers
3. Connect High Voltage **PHASE A** to **X4** on transformer A
4. Connect High Voltage **PHASE C** to **X4** on transformer B
5. Connect Low Voltage **PHASE A** to **H4** and **X1** on transformer A
6. Connect Low Voltage **PHASE C** to **H4** and **X1** on transformer B
7. Connect High & Low Voltage **PHASE B** to **H1**
8. Bridge **H1** connections between transformer A & B

### DIAGRAM G2

#### HIGH VOLTAGE





sales@sanzosales.com

The image shows two identical large, grey, rectangular autotransformers from Sanzo Sales. Each unit features a lifting eye at the top and a detailed technical label. The label for the unit on the left specifies a model of TX-BB-208D-240D-23.4A, a 230V input, and a 240V output. The unit on the right is labeled TX-BB-208D-240D-23.4A and also specifies a 230V input and 240V output. Both units are equipped with a 100A primary and a 100A secondary, and are rated for 100KVA. The labels also include safety warnings and a warning symbol.

**sales@sanzosales.com**



*Base Knockouts — (4) ¾" NPT*



*Side View*



*Rear View — Surface Mount Bracket*



Wiring Compartment — Terminal Leads



*Interior — Epoxy Resin Encapsulated Core*