Connection Guide

1. Connect **X4** and **X3** together for each transformer
2. Connect **X2** and **X1** together for each transformer
3. Connect High Voltage **PHASE A** to **X4, X3** on transformer A
4. Connect High Voltage **PHASE C** to **X4, X3** on transformer B
5. Connect Low Voltage **PHASE A** to **X1, X2, H4, H3** on transformer A
6. Connect Low Voltage **PHASE C** to **X1, X2, H4, H3** on transformer B
7. Connect High & Low Voltage **PHASE B** to **H1** and **H2**
8. Bridge **H1** and **H2** connections between Transformers A & B

DIAGRAM F2

